


13.3 INCH VGA/HDMI/AV/BNC/USB LED COLOR MONITOR



OPERATION INSTRUCTION

Connection guide



Port Connection

- POWER SUPPLY : DC 12V
- VGA :VGA image input
- HDMI : HDMI image input
- AV: Video image input
- L:Left channel sound input
- R:Right channel sound input
- USB :USB reader input (USB touch optional)
- BNC input : CCTV security BNC input


Key button function

SOURCE :Mode Switch (VGA/HDMI/AV/BNC/USB)

MENU :Press the menu key to enter the menu operating system, then press menu key choose the "picture mode" or "other option", then press "<" or ">" enter the drop-down options, after that press "<" and ">" to select left and right and adjust, and then press the menu key to select up and down.

POWER:Single press once to enter power on, then the indicator light will be blue, press again to enter standby, then the indicator light will be red.

IR: Remote receiver window



Remote control panel



Liustrations of the remote controller

MUTE : Enable/disable the sound output

SELECT: Mode Switch (VGA/HDMI/AV/BNC/USB)

POWER : Power switch button, turn the machine on or off

EXIT : Exit the operation

MENU : View the system menu

OK : Confirm selection

▲▼ : Select up and down

◀▶ : Adjust left and right

■ : Stop playback

⏮⏭ : Pause or resume playback

⏮ : Previous track

⏭ : Next track

⏮⏭ : Fast forward

⏮ : Rewind

VOL+ : Volume+

VOL- : Volume-

Specification

Display Size:13.3 inch

Screen Ratio :16:9 widescreen

Display area:296(L)x165(w)mm

Monitor size : 324(L)x199(w) mm

View Angle:85/85/85/85

Contrast:800:1

Brightness : 250cd/m2 (300cd/m2 /400cd/m2/450cd/m2 optional)

Native Resolution:1366*768

Support:Supports multiple resolution displays

Av Chromatic:PAL/NTSC (auto switch)

HDMI MODE support:720P/1080P

Voltage: DC 12V (around 10W)

Working Temperature:-10°C~60°C

Control:Button control

Feature:Bright color, clear picture,less consumption